


SPECIFICATION	CONNECTION	VALUE	NOTES:				
RATED VOLTAGE(V):		110	1.THE LEAD WIRE OF BIG MOTOR CAN NOT BE PULLED FORCIBLY TO AVOID INTERNAL POOR CONDUCTIVITY.				
NO LOAD CURRENT(mA):		≤500	2.PREVENT GEAR MOTOR FROM BEING SHOCKED OR DROPPING IN MOUNTING PROCESS.IT IS PROHIBITED TO STRIKE AND CRUSH DIRECTLY ON REDUCER OUTPUT SHAFT.				
NO LOAD SPEED(RPM):		10±1	3.IT IS NECESSARY TO BE CAREFUL THAT THE ADHESIVE DOES NOT SPREAD ALONG THE SHAFT AND FLOW INTO THE BEARING.				
RATED LOAD TORQUE(kgf.cm):		40	4.DO NOT TURN A GEARED MOTOR BY ITS OUTPUT SHAFT WHEN,FOR EXAMPLE,ARRANGING ITS POSITION SO AS TO INSTALL IT.				
RATED CURRENT(mA):		≤550	5.USE WITH A LOAD THAT EXCEEDS THE RATED TORQUE WILL BE REDUCE THE LIFETIME OF GEAR MOTOR.				
RATED LOAD SPEED(RPM):		8±0.8	6.CHECK MOTOR RUNNING WHEN IT IS POWER ON BEFORE INSTALLATION AND MAKE SURE PERFORMANCE MEET REQUEST .				
STALL CURRENT(mA):		—					
STALL TORQUE(kgf.cm):		—					
ROTATION DIRECTION		CW/CCW					
				APVD	LDJ	9.22.2023	AC GEARBOX MOTOR
				CHKD			
			1:1	DRN	ZPJ	9.22.2023	FGF-6130-110V-G277
			SCALE	SIGNATURE		DATE	